

On the algebraic Riccati equation

Harald K. Wimmer

In this note the matrix equation $A + WB + B^T W + WCW = 0$ is considered. A monotoneity result and an inertia theorem on the location of the eigenvalues of W and $B + CW$ are proved.

1. A monotoneity result

We study the algebraic Riccati equation

$$(1) \quad A + WB + B^T W + WCW = 0,$$

where all matrices are $n \times n$ and real, and A , C , and W are symmetric. We assume

$$(2) \quad C \leq 0 \text{ (negative semidefinite)}$$

and

$$(3) \quad (B, C) \text{ controllable.}$$

[See the next section for the definition of controllability.] Coppel [4] has given a comprehensive algebraic theory of (1) on which we base our note.

We recall the following results from [4]. If (1) is solvable, then there exists a maximal solution W_+ ; that is, $W_+ \geq \tilde{W}$ for each solution \tilde{W} of (1). If M ,

$$M = \begin{pmatrix} B & C \\ -A & -B^T \end{pmatrix},$$

has no eigenvalues on the imaginary axis, then there exists a solution of

Received 11 March 1976. This research was supported by the Alexander von Humboldt-Stiftung.

(1) and $B + CW$ is a stable matrix (that is with all eigenvalues in the left half plane), if and only if $W = W_+$. Set

$$H = \begin{pmatrix} A & B^T \\ B & C \end{pmatrix}.$$

Then (1) can be written as

$$(I \ W)H \begin{pmatrix} I \\ W \end{pmatrix} = 0.$$

THEOREM 1. *Let M have no eigenvalues on the imaginary axis and let W_+ be the maximal solution of (1). If W_1 is a solution of*

$$(4) \quad A_1 + W_1 B_1 + B_1^T W_1 + W_1 C_1 W_1 = 0,$$

and

$$H = \begin{pmatrix} A & B^T \\ B & C \end{pmatrix} \geq H_1 = \begin{pmatrix} A_1 & B_1^T \\ B_1 & C_1 \end{pmatrix},$$

then $W_+ \geq W_1$.

Proof. H_1 can be written as $H_1 = H - \tilde{H}$, $\tilde{H} \geq 0$. Thus (4) is equivalent to

$$A + W_1 B + B^T W_1 + W_1 C W_1 = (I \ W_1) \tilde{H} \begin{pmatrix} I \\ W_1 \end{pmatrix} = R \geq 0.$$

For $D = W_+ - W_1$ we obtain

$$D(B + C W_+) + (B + C W_+)^T D = D C D - R$$

which is a Ljapunov matrix equation with $B + C W_+$ stable and $D C D - R \leq 0$. Hence $D \geq 0$. This theorem generalizes a result in [7] where monotoneity with respect to A was proved.

2. An inertia theorem

We shall need the following lemmas and definitions. The pair (F, G) , $F \in \mathbb{C}^{n \times n}$, $G \in \mathbb{C}^{n \times m}$, is called controllable (Hautus [5]), if

$$(5) \quad \text{rank}(G, FG, \dots, F^{n-1}G) = n .$$

The pair $\begin{pmatrix} F \\ K \end{pmatrix}$, $K \in \mathbb{C}^{p \times n}$, is called observable [2], if $\begin{pmatrix} F^T & K^T \end{pmatrix}$ is controllable.

LEMMA 1 (Hautus [5]). *The pair $\begin{pmatrix} F \\ K \end{pmatrix}$ is observable, if and only if for $\lambda \in \mathbb{C}$, $y \in \mathbb{C}^n$,*

$$Fy = \lambda y, \quad Ky = 0 \Rightarrow y = 0 .$$

For a complex $n \times n$ matrix F the inertia, $\text{in } F$, of F is defined [6] as the triple

$$\text{in } F = \{\pi(F), \nu(F), \delta(F)\}$$

where $\pi(F)$, $\nu(F)$, and $\delta(F)$ are respectively the number of eigenvalues of F with positive, negative, and vanishing real part.

LEMMA 2 ([3], [8]). *Let F, W , and S be real $n \times n$ matrices, S and W symmetric. If $S \leq 0$ and $\begin{pmatrix} F \\ S \end{pmatrix}$ is observable and*

$$WF + F^T W = S ,$$

then

$$(a) \quad \text{in } F = \text{in}(-W) \quad \text{and} \quad \delta(F) = \delta(W) = 0 ,$$

and especially

$$(b) \quad F \text{ is stable, if and only if } W > 0 .$$

The following inertia result is obtained under additional assumptions on the coefficient matrices of (1).

THEOREM 2. *Assume $C \leq 0$, (B, C) controllable,*

$$(6) \quad A \geq 0$$

and

$$(7) \quad \begin{pmatrix} B \\ A \end{pmatrix} \text{ observable.}$$

Then

$$(a) \quad \text{there exists a solution of (1), and}$$

(b) for each solution W ,

$$\text{in}(B+CW) = \text{in}(-W) \text{ and } \delta(B+CW) = \delta(W) = 0$$

holds.

Proof. (a) We show that $\delta(M) = 0$, which implies the existence of a solution. Suppose $i\alpha$, α real, is an eigenvalue of M with eigenvector $\begin{pmatrix} r \\ s \end{pmatrix}$; that is,

$$(8) \quad M \begin{pmatrix} r \\ s \end{pmatrix} = i\alpha \begin{pmatrix} r \\ s \end{pmatrix}, \quad \begin{pmatrix} r \\ s \end{pmatrix} \neq \begin{pmatrix} 0 \\ 0 \end{pmatrix}.$$

Premultiplying both sides of (8) by (s^*, r^*) , we get

$$s^*Cs - r^*Ar + (s^*Br - r^*B^T s) = i\alpha(s^*r + r^*s),$$

and, separating real and imaginary parts, we obtain

$$s^*Cs - r^*Ar = 0.$$

(2) and (6) imply $Cs = 0$ and $Ar = 0$. Now (8) yields $Br = i\alpha r$ and $B^T s = -i\alpha s$. Thus $\begin{pmatrix} B - i\alpha I \\ A \end{pmatrix} r = 0$, and since $\begin{pmatrix} B \\ A \end{pmatrix}$ is assumed to be observable, we deduce from Lemma 1 that $r = 0$. Similarly $s = 0$. Therefore $i\alpha$ can not be an eigenvalue of M . A different proof that there exists a solution W relies on optimal control theory and can be found in [2].

(b) Let W be a solution of (1). Then

$$W(B+CW) + (B+CW)^T W = WCW - A.$$

From $(WCW-A)q = 0$ we get $CWq = 0$ and $Aq = 0$. Therefore $(B+CW)q = \lambda q$ and $(WCW-A)q = 0$ implies

$$(9) \quad Bq = \lambda q, \quad Aq = 0.$$

Because of (7) and (9) we have $q = 0$ and the pair $\begin{pmatrix} B+CW \\ WCW-A \end{pmatrix}$ is also observable. The conditions of Lemma 2 are satisfied and the statement of the inertia follows.

One of the problems which lead to (1) with coefficients satisfying (3), (4), (6), and (7) is the output regulator problem over an infinite time interval (see [1]). This close connection between optimal control

theory and the algebraic Riccati equation has been used to establish the following result (see [2]), for which an algebraic proof is now immediate.

THEOREM 3 ([2]). *Let (1) be given together with (3), (4), (6), and (7). Then W_+ is the only positive definite solution of (1).*

Proof. Since $B + CW_+$ is stable, $W_+ > 0$ follows from Theorem 2 (b). Conversely, if $W > 0$, then by the same theorem $A + CW$ is stable, which is only possible for $W = W_+$.

References

- [1] Michael Athans, Peter L. Falb, *Optimal control. An introduction to the theory and its applications* (McGraw-Hill, New York, St. Louis, San Francisco, Toronto, London, Sydney, 1966).
- [2] Roger W. Brockett, *Finite dimensional linear systems* (John Wiley & Sons, New York, London, Sydney, Toronto, 1970).
- [3] Chi-Tsong Chen, "A generalization of the inertia theorem", *SIAM J. Appl. Math.* 25 (1973), 158-161.
- [4] W.A. Coppel, "Matrix quadratic equations", *Bull. Austral. Math. Soc.* 10 (1974), 377-401.
- [5] M.L.J. Hautus, "Controllability and observability conditions of linear autonomous systems", *Proc. K. Nederl. Akad. Wetensch. Amsterdam Ser. A* 72 (1969), 443-448.
- [6] Alexander Ostrowski and Hans Schneider, "Some theorems on the inertia of general matrices", *J. Math. Anal. Appl.* 4 (1962), 72-84.
- [7] Jan C. Willems, "Least squares stationary optimal control and the algebraic Riccati equation", *IEEE Trans. Automatic Control* AC-16 (1971), 621-634.
- [8] Harald K. Wimmer, "Inertia theorems for matrices, controllability, and linear vibrations", *Linear Algebra and Appl.* 8 (1974), 337-343.

Mathematisches Institut der Universität,
Würzburg,
Germany;

Mathematisches Institut,
Technische Universität Graz,
Graz,
Austria.